



Sat-Light Platinum Series

PL7630 55dB Gain RF Amplifier



Features & Benefits

- Covers the entire frequency of the Sat-Light/Platinum suite [10 – 3000 MHz]
- Adjustable gain [55dB maximum] via a local LCD or a SNMP card
- Embedded input/output RF power meter
- High output 1dB compression point +12dBm
- Powerful management capabilities via a front panel LCD and rack mounted SNMP

Product Description

Global Foxcom's Sat-Light/Platinum's **PL7630** RF Amplifier provides the capability to integrate a pre- or post-amplifier as a part of the IFL system. Using an RF Amplifier enables a full system solution with guaranteed overall system performance over long distances.

As a Pre-amplifier **PL7630** ensures a high C/N by providing the optical transmitter with sufficient RF to optimally drive the laser.

As a Post amplifier **PL7630** assures a constant high signal level RF output.

PL7630 has an integral input/output RF power meter and is fully compatible with the Sat-Light/Platinum M&C SNMP system.

Sat-Light Platinum Series

Specifications

RF Specifications	Units	Typical	Minimum	Maximum
Frequency Range Bandwidth	MHz	10–3000		3000
Amplitude Response 10 - 3000 MHz any 36 MHz	dB	±1.5 ±0.25		±2 ±0.3
Gain	dB			55
Gain – Range of Adjustment ¹	dB		25	55
Gain Stability	dB/24hr	±0.2		±0.25
Gain Slope	dB			+1.0
Gain Variation over temperature	dB	±1.5	-2	2
SFDR ²	dB/Hz ² / ³	98		
DR (Dynamic Range–single channel) ¹	dB			30
CNR [any 36 MHz] ²	dB	70		
Noise Figure (NF) max. gain ³	dB	5		5
Noise Figure (NF)min. gain ⁴	dB	5		5
Output IP3 (OIP3)	dBm			
Group Delay Variation–linear 10 to 60 MHz 60 to 3000 MHz	ns	20 2		
Input/Output Impedance	Ohm	50 or 75		
Input 1dB Compression Point ⁵	dBm	-43		-42
Input Signal Range–Total Power ⁶	dBm		None, LED limit -61dBm with 25dB Gain	-50dBm @ Max Gain -20dBm @ Min Gain
Maximum Input without damage ⁵	dBm			-20
RF Output Signal Range [Total power]	dB			5
Input/Output Return Loss 50 Ohm 75 Ohm ⁷	dB	-15 -13		-15 -13
RF Connector Input / Output	Type	F, SMA, BNC, N		
Electrical Specifications				
Supply Voltage	VDC	12		
Supply Current ⁸	Amps	0.5		
EMI Rating	EMI Rating: FCC Class B. CE Mark			
Physical / Environmental Specifications				
Operating Temperature Range	°C		-10	+55
Storage Temperature Range	°C		-45	+85
Relative Humidity		95% non-condensing		
Altitude	ft / Km	10,000 [3.08] operating ¹⁰ 14,000 [12.2] non-operating		
Dimensions [D×W×H]	ins/cm	12×0.8×4 / 30.5×2×10.2		
Weight	lbs./Kg	0.5 / 0.23		
MTBF	Hours	TX: 309, 481 RX: 359, 057		
MTTR	Hours	0.083		
Shock & Vibration	Designed for normal transportation environment per section 514.4 MIL-STD-810E.			

Sat-Light Platinum Series

Designed to withstand 20G at 11 ms [½ sine pulse] in non-operating configuration.

1. User adjustable
2. -55 dBm RF input, gain = 55 dB, IMD=-55 dBc
3. -55 dBm RF input, gain =55 dB
4. -55 dBm RF input, gain =30 dB
5. @ Max. gain
6. @ Max. gain, Alarm trip point: Red -40 dBm, Amber -58 dBm
7. -13 dB @ 10 to 2500 MHz, -10 dB @ 2500 to 3000 MHz
8. With standard adiabatic derating at 2°C/1000ft. [0.3 Km.]

All specifications are subject to change without notice.

Ordering Information Matrix for PL7630 RF Amplifier

Example: PL7230T-50SMA-SC

L-band, high RF input transmitter, 1310 nm laser, 50-Ohm SMA RF connector and SC/APC optical connector

PL7

2	3	0	T	Null	-	50SMA	-	SC
A	B	C	D	E		F		G

A Platinum Product

- 00 - MCP
- 01 - Chassis & PS
- 0 - 5 MHz Tx/Rx
- 1 - 10 MHz Tx/Rx
- 2 - L-Band Tx/Rx
- 3 - IF Tx/Rx
- 4 - Wideband Tx/Rx
- 5 - Data XVCR
- 6 - Accessories
- 7 - Non-chassis mount products

B Tx RF Input/ Rx RF output

- 2 - Low power input
- 3 - High power input

C Product Series

- Null - None [default]
- 1 - 1st series
- 2 - 2nd series
- Etc.

D Module Type

- T = Tx
- R = Rx
- S = Serial data
- E = Ethernet
- G = GigE

F RF Connector

- 75F = 75-Ohm F
- 75BNC = 75-Ohm BNC
- 50BNC = 50-Ohm BNC
- 50SMA = 50-Ohm SMA
- 50N = 50-Ohm N

E Laser for TX & Optical budget for RX

- Tx: Null = 1310nm laser
- 1550 = 1550nm laser
- XXXX = ITU option
- Rx: 4= 4dB 16=16dB
- 10=10dB 25= 25dB

G Optical Connector

- Null = FC/APC [default]
- SC = SC/APC
- E2 = E2000